



RUR5

B70UF DIP SWITCHES SETTING : 1

Supported bill Ruble (old,new-10, 50, 100, 500, 1000) 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Ruble 10	OFF	OFF	OFF							
	2 Pulse / Ruble 10	OFF	OFF	ON							
	3 Pulse / Ruble 10	OFF	ON	OFF							
	4 Pulse / Ruble 10	OFF	ON	ON							
	5 Pulse / Ruble 10	ON	OFF	OFF							
	10 Pulse / Ruble 10	ON	OFF	ON							
	20 Pulse / Ruble 10	ON	ON	OFF							
	100 Pulse / Ruble 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept Ruble 10(old,new)						ON				
	Reject Ruble 10(old,new)						OFF				
★	Accept Ruble 50(old,new)							ON			
	Reject Ruble 50(old,new)							OFF			
★	Accept Ruble 100(old,new)								ON		
	Reject Ruble 100(old,new)								OFF		
★	Accept Ruble 500(old,new)									ON	
	Reject Ruble 500(old,new)									OFF	
★	Accept Ruble 1000(old,new)										ON
	Reject Ruble 1000(old,new)										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
	Pulse Protocol		ON		
	ICT Protocol		OFF		
	HOLD			ON	
				OFF	
					ON
					OFF

